

Product Code: CSP032

Description: Smart PIR



### General Information

|                                     |                            |   |
|-------------------------------------|----------------------------|---|
| <b>Dimensions (mm)</b>              | 33 (W) x 33 (D) x 39.5 (H) |   |
| <b>Finish</b>                       | White                      |   |
| <b>Materials</b>                    | Housing: Polycarbonate     | Electronics: PCB & Electronic Components    |
| <b>Rated Voltage (DC)</b>           | 3                          |   |
| <b>Battery Type</b>                 | CR 2450 (Supplied)         |   |
| <b>Battery Lifetime (Approx.)</b>   | 1 Year (Dependent On Use)  |   |
| <b>Protocol</b>                     | Zigbee                     | <b>Signal Transmission Frequency</b> 2.4GHz |
| <b>Sensor</b>                       | Infrared                   |   |
| <b>Detection Range (M)</b>          | 7                          |   |
| <b>Detection Angle (°)</b>          | 170                        |   |
| <b>Rotation (°)</b>                 | 360                        |   |
| <b>Tilt Angle (°)</b>               | 90                         |   |
| <b>Indicator Colour</b>             | Blue                       |   |
| <b>Ingress Protection</b>           | IP20                       |   |
| <b>Working Humidity</b>             | 10%-90%RH                  |   |
| <b>Operational Temperature (°C)</b> | -10 to +50                 |   |
| <b>Warranty (Years)</b>             | 1                          |   |

**Additional Information** For cleaning / polishing of products, use only a soft, dry, clean cloth. Control linked receivers through the ClickSmart+ app. Send activation alerts to your phone.

**Components Supplied** Smart PIR Reset Key Instruction Manual

**Installation Overview** Suitable for ceiling or wall mounting. Self-adhesive pad applied ready for installation.

**Programming Information** With hub and app setup with PIR having battery installed, using the pin supplied press the reset button for five seconds and the PIR LED will start flashing. Can be paired with hub via app.