

Toughbay™ Pro

150W / 115W / 80W (5700K)

NEW

- Plug and play Microwave and PIR module options available
- Wattage selectable via a simple switch, 150W/115W/80W
- Available in 60°, 90° and 120° beam angles
- 1-10V dimmable as standard
- Remote control available to control PIR on/off, MW on/off and MW step dim (LEV71808)
- Ultra efficient, up to 150 Lumens per circuit Watt
- IP65 emergency option with wide 130° angle
- Surface mount bracket also available
- 5-year warranty including 1 year on-site



Rating



Class 1



Wattage
switchable



CRI: Ra



Warranty*



On-site




Beam
options




Emergency
options

149.9mm



240mm
Standard

198mm



270mm
Emergency

CODE	DESCRIPTION	COL TEMP.	DIM.	WATT	LUMENS
JC040206	Toughbay Pro 60° 1-10V Dimmable	5700K	Yes	150W/115W/80W	Up to 21,200
JC040207	Toughbay Pro 60° 1-10V Dimmable Self-Test Emergency	5700K	Yes	150W/115W/80W	Up to 21,200
JC040208	Toughbay Pro 90° 1-10V Dimmable	5700K	Yes	150W/115W/80W	Up to 21,200
JC040209	Toughbay Pro 90° 1-10V Dimmable Self-Test Emergency	5700K	Yes	150W/115W/80W	Up to 21,200
JC040210	Toughbay Pro 120° 1-10V Dimmable	5700K	Yes	150W/115W/80W	Up to 21,200
JC040211	Toughbay Pro 120° 1-10V Dimmable Self-Test Emergency	5700K	Yes	150W/115W/80W	Up to 21,200
JC040224**	Surface Mount bracket for Toughbay Pro	-	-	-	-
JC040225	Surface Mount bracket for Toughbay Pro Emergency	-	-	-	-
JC040226	Toughbay Pro Polycarbonate Prismatic Reflector	-	-	-	-
LEV71950	Toughbay Pro PIR Dim Sensor IP65	-	-	-	-
LEV71951	Toughbay Pro Microwave Dim Sensor IP65	-	-	-	-
LEV71808	Remote control for Toughbay Pro MW and PIR sensors	-	-	-	-

Body: Aluminium. **Lens:** Polycarbonate. **Bracket:** Steel.

**JC040224 mount bracket not suitable for use with emergency or microwave step dim versions.