

# **Technical Specification**

A Scolmore GROUP Company

Product Code: ECSPK6

**Description:** Smart Security Kit 6



#### Kit Part: Smart Hub

General Information

Sounder Output 95dB
Maximum Devices 32
Kit Warranty 1 Year

Transmission

Router Transmission 2.4GHz (IEEE 802.11 b/g/n)
Router Transmission Range 150m (Open Field)

Auxilliary

GSM Yes; Full-size SIM

**GSM Frequency** 850 / 900 / 1800 / 1900 MHz

Construction

Material ABS
Fixing Surface
Colour White

Programming

Available Operations Home/Arm/Disarm/SOS

## Kit Part: Remote Control

Transmission Frequency 433 MHz
Transmission Range 80m (open field)

Material ABS Colour Black

Available Operations Home/Arm/Disarm/SOS Operating Voltage (DC) 3V (CR2025 Battery)

Consumption <7mA

Power Reserve Approx. 12 Months

Relative Humidity <80% (non-condensing)

Dimensions 57mm x 31mm x 11mm

Weight 20g

#### Kit Part: PIR

Number of PIRs 2

PIR Range 8m

Transmission Frequency 433 MHz

Transmission Range 80m (open field)

Material ABS
Fixing Surface
Colour White

**Zone Types** Normal Sensor/24h mode/Delay mode/Home

mode/24h mute sensor/Home delay mode

Operating Voltage (DC) 3V (2 x AA Batteries)

Consumption 0.0095A

Power Reserve Approx. 12 Months
Battery Type 3 x AA (LR06)

Weight 46g

Operating Temperature -10°C - 55°C

Relative Humidity < 80% (non-condensing)
Dimensions 107mm x 53mm x 32mm
Bracket Dimensions 52mm x 30mm x 26.5mm

### Kit Part: Door/Window Contact

Transmission Frequency 433 MHz
Transmission Range 80m (open field)

Material ABS
Fixing Surface

Colour White

Zone Types Normal Sensor/24h mode/Delay mode/Home

mode/24h mute sensor/Home delay mode

Operating Voltage (DC) 3V (CR2477)

Consumption 0.015A

Power Reserve Approx. 12 Months

**Battery Type** CR2477 **Operating Temperature** -10°C - 55°C

Relative Humidity <80% (non-condensing)
Dimensions 55.7mm x 30.3mm x 16mm
Magnet Dimensions 25mm x 10mm x 9mm

Weight 20g

## Components Supplied

Fort Hub, Fort Pet PIR x 2, Fort Door/Window Contact x 2, Fort Remote Control x 2, AC Adapter, Product Batteries, Mounting Screws & Wall plugs, User Guides